



Emergency Ballasts

Linear Fluorescent

LP500



Project: _____
Type: _____
Model No: _____ Qty: _____
Date: _____
Notes: _____

Low-Profile for Space-Limited Fixtures
Operates 21 - 54 W T5 (2'-4') Lamps or
32 W (4') T8 Lamps
Damp Locations

Product order number: LP500M (galvanized metal case)

Specifications

UL LISTED

Factory or Field Installation

Illumination Time

90 Minutes

Initial Light Output

400 - 700 Lumens @ 25°C

Full Warranty

5 Years (NOT pro-rata)

Dual Input Voltage

120/277 VAC, 60 Hz

AC Input Current

140 mA

AC Input Power Rating

1.5 Watts

Test Switch

Single Pole

Battery

High-Temperature, Maintenance-Free
Nickel-Cadmium Battery
7- to 10-Year Life Expectancy

Battery Charging Current

115 mA

Recharge Time

24 Hours

Charging Indicator Light

LED

Temperature Rating (Ambient)

0°C to +50°C (32°F to 122°F)

Dimensions

18.5" L x 1.18" W x 1" H
(470 mm x 30 mm x 25 mm)
Mounting Center 18.1" (460 mm)

Weight





2.1 lbs. (.95 kg)

Benefits:

- Low Profile case
- Emergency mode lumen output up to 700 lumens
- End-of-Lamp-Life Compatible

Dimensions

18.5" x 1.18" x 1.0" (mounting center - 18.1")



A test switch and charging indicator light is provided.



LP500

Flourescent Emergency Ballast, Low-Profile for Space-Limited Fixtiures

Table 1 Lamp Compatibility

LAMP	LUMENS
F54T5HO	600
F28T5	520
F21T5	400
F32T8	700

APPLICATION

The LP500 low-profile emergency ballast works in conjunction with a low-profile or standard-size AC ballast to convert new or existing T5 and T8 fluorescent fixtures into unobtrusive emergency lighting. The emergency ballast consists of a high-temperature nickel-cadmium battery, charger and electronic circuitry in one compact case. The LP500 can be used with one 21 through 54 W (2'-4') T5 fluorescent lamp or 32 W (4') T8 lamp and is compatible with most electronic and dimming AC ballasts. If used in an emergency-only fixture, no AC ballast is necessary. The LP500 is suitable for indoor and damp locations and for sealed and gasketed fixtures, including fixtures rated for wet locations. It is not suitable for air handling heated air outlets or wet or hazardous locations. For information about specific lamp and ballast compatibility, please call the factory. Recommended applications include: emergency lighting for pendant, cove, recessed indirect/direct, surface-mount and architectural lighting commonly used in office, hospitality, health care, retail and educational facilities.

OPERATION

When AC power fails, the LP500 immediately switches to the emergency mode, operating one lamp at a reduced lumen output for a minimum of 90 minutes. When AC power is restored, the emergency ballast automatically returns to the charging mode and, using a patented circuit, delays AC ballast operation for approximately three seconds to prevent false tripping of the AC ballast end-of-lamp-life shutdown circuits.

INSTALLATION

The LP500 does not affect normal fixture operation and may be used with either a switched or unswitched fixture. If a switched fixture is used, an unswitched hot lead must be connected to the emergency ballast. The emergency ballast must be fed from the same branch circuit as the AC ballast. The LP500 may be installed inside or on top of the fixture. Installation is not recommended with fixtures where the ambient temperature may fall below 0° C.

EMERGENCY ILLUMINATION

Depending on the wattage and type of lamp selected, the LP500 produces 400 to 700 lumens initial emergency light output. During emergency operation, one lamp is illuminated, even if installed with a multi-lamp AC ballast.

SPECIFICATION

Emergency lighting shall be provided by using a standard fluorescent fixture equipped with a Philips Bodine LP500 low-profile emergency ballast. The LP500 shall consist of a high-temperature, maintenance-free nickel-cadmium battery, charger and electronic circuitry contained in one 18.5" x 1.18" x 1" galvanized steel case. A solid-state charging indicator light to monitor the charger and battery, a single-pole test switch and installation hardware shall be provided. The emergency ballast, using a patented circuit, shall delay AC ballast operation for approximately three seconds to prevent false tripping of AC ballast end-of-lamp-life shutdown circuits. The emergency ballast shall

be capable of operating one _____ fluorescent lamp at _____ lumens (see Table 1) initial light output in the emergency mode for a minimum of 90 minutes. It shall be suitable for indoor locations. The LP500 shall have 1.5 Watts of input power and a 10.8 Watt-hour battery capacity and shall exceed emergency standards set forth by the current NEC. The emergency ballast shall be UL Listed for installation inside or on top of the fixture.

WARRANTY

Model LP500 is warranted for five (5) full years from date of purchase. Please see detailed warranty information on our web site.

